

FEATURES

- Easy & low torque engagement
- Leak free assembly and reassembly
- Various patterns & connections
- Wide variety of materials

APPLICATION

- Oil & Gas industries
- Petrochemical / Chemical processing
- Shipbuilding & Heavy industrial industries
- Power generation, Pulp & paper industries
- Cryogenic & semiconductor industries
- Research laboratories



ORDERING CODES

1. PRODUCT CODE

CODE	Tube	Thread	CODE	Tube	Thread
Dimensions, mm			Dimensions, inch		
M60-11N	6	1/8" NPTM	I18-11N	1/8	1/8" NPTM
M60-12N	6	1/4" NPTM	I18-12N	1/8	1/4" NPTM
M60-14N	6	1/2" NPTM	I14-11N	1/4	1/8" NPTM
M80-11N	8	1/8" NPTM	I14-12N	1/4	1/4" NPTM
M80-12N	8	1/4" NPTM	I14-14N	1/4	1/2" NPTM
M80-14N	8	1/2" NPTM	I14-15N	1/4	3/4" NPTM
M10-11N	10	1/8" NPTM	I12-12N	1/2	1/4" NPTM
M10-12N	10	1/4" NPTM	I12-14N	1/2	1/2" NPTM
M10-14N	10	1/2" NPTM	I12-15N	1/2	3/4" NPTM
M12-12N	12	1/4" NPTM	I12-16N	1/2	1" NPTM
M12-14N	12	1/2" NPTM	I34-14N	3/4	1/2" NPTM
M12-15N	12	3/4" NPTM	I34-15N	3/4	3/4" NPTM
M16-13N	16	3/8" NPTM	I34-16N	3/4	1" NPTM
M16-14N	16	1/2" NPTM	I11-14N	1	1/2" NPTM
M16-15N	16	3/4" NPTM	I11-15N	1	3/4" NPTM
M20-14N	20	1/2" NPTM	I11-16N	1	1" NPTM
M20-15N	20	3/4" NPTM			
M25-15N	25	3/4" NPTM			
M25-16N	25	1" NPTM			
M25-15N	25	3/4" NPTM			

M60-11N

2. MATERIAL

MA	Brass
MC	AISI 304 SS
MD	AISI 304L SS
MF	AISI 316 SS
MG	AISI 316L SS
MM	Monel 400
MN	Monel K-500
MO	Hastelloy C-276

MA

Ordering Example : F204-M60-11N-MA

NOTES:

1. Change 10th character to B for BSP threads.
2. Change 10th character to M for Metric treads, check factory for details.